



ANNUAL MAINTENANCE CHECKLIST

This checklist is intended as a guide to help plan and track the scheduled maintenance activities for your Real Power generator through each calendar year. Always interpret the “frequency” directions on the far right column to be the lesser of the two options. Refer back to your owner’s manual for more information on each service item.



Before performing any maintenance on any portion of the Real Power generation system, the vehicle must be off with the keys removed from WARNING: the ignition and the generator and all parts of the vehicle must be allowed to cool down after use.

1	2	3	4	5	6	7	8	9	10	11	12	Component(s)	Maintenance Item	Frequency
												Drive Shaft	Lubricate 4x4 Ball Joint	60hrs / 1 Month
												Drive Shaft	Lubricate Slip Joint Zerk Fitting	100hrs / 1 Month
												Drive Shaft	Inspect U-Joints and Carrier Bearing	100hrs / 1 Month
												Drive Shaft & PTO	Check paint indicators on fasteners	100hrs / 1 Month
												PTO & Generator	Free Rotation Check	100hrs / 1 Month
												Generator	Remove and Wash Air Filter	300 hrs
												Generator	Full visual inspection	1 year
												Drive Shaft	Full visual inspection	1 year
												Drive Shaft & PTO	Check fasteners	1 year
												Panel	Internal Inspection	1 year
												Truck	Engine Oil Change	5000-7500 miles*
												Truck	Fuel Filter	20,000miles**
												Truck	Transmission Fluid Replacement	150,000 miles**

*As indicated by vehicle oil life monitoring system

**Include generator hours x 50 miles/hr calculation

Signature

Date Completed